

**Proposed
Draft**

**Serial ATA
International Organization**

**Version 1.0
April 18, 2007**

**Serial ATA Revision 2.6 ECN # 009
Title : Correcting LBP references in the COMP
data pattern and other locations**

This is an internal working document of the Serial ATA International Organization. As such, this is not a completed standard and has not been approved. The Serial ATA International Organization may modify the contents at any time. This document is made available for review and comment only.

Permission is granted to the Promoters, Contributors and Adopters of the Serial ATA International Organization to reproduce this document for the purposes of evolving the technical content for internal use only without further permission provided this notice is included. All other rights are reserved and may be covered by one or more Non Disclosure Agreements including the Serial ATA International Organization participant agreements. Any commercial or for-profit replication or republication is prohibited. Copyright © 2000-2007 Serial ATA International Organization. All rights reserved.

This Draft Specification is NOT the final version of the Specification and is subject to change without notice. A modified, final version of this Specification ("Final Specification") when approved by the Promoters will be made available for download at this Web Site: <http://www.serialata.org>.

THIS DRAFT SPECIFICATION IS PROVIDED "AS IS" WITH NO WARRANTIES WHATSOEVER, INCLUDING ANY WARRANTY OF MERCHANTABILITY, NON-INFRINGEMENT, FITNESS FOR ANY PARTICULAR PURPOSE OR ANY WARRANTY OTHERWISE ARISING OUT OF ANY PROPOSAL, SPECIFICATION, OR SAMPLE. Except for the right to download for internal review, no license, express or implied, by estoppel or otherwise, to any intellectual property rights is granted or intended hereunder.

THE PROMOTERS DISCLAIM ALL LIABILITY, INCLUDING LIABILITY FOR INFRINGEMENT OF ANY PROPRIETARY RIGHTS, RELATING TO USE OF INFORMATION IN THIS DRAFT SPECIFICATION. THE PROMOTERS DO NOT WARRANT OR REPRESENT THAT SUCH USE WILL NOT INFRINGE SUCH RIGHTS.

THIS DOCUMENT IS AN INTERMEDIATE DRAFT FOR COMMENT ONLY AND IS SUBJECT TO CHANGE WITHOUT NOTICE.

* Other brands and names are the property of their respective owners.

Copyright © 2005-2007 Serial ATA International Organization. All rights reserved.

Author Information

Author Name	Company	Email address
Jef Wolford	Hewlett Packard	Jeff.wolford@hp.com

Workgroup Chair Information

Workgroup (Phy, Digital, etc...)	Chairperson Name	Email address
Phy	Chuck Hill	cphill@altaeng.com

Document History

Version	Date	Comments
0.1	April 4 th , 2007	Initial release.
0.2	April 9 th , 2007	Added removal of NOTE and redundant LBP text definition, corrected accidental removal of D20.2 Dword following the updated RD- LBP.
1.0	April 18, 2007	Corrected (changed 128 to 8) LBP multiplier in RD+ short version total summary Corrected Corrected 2 spelling mistakes Corrected color of single bit background ECN-18 information
	April 18, 2007	Phy WG approval

1 Introduction

1.1 Problem Statement:

- 1) With the approval of SATA 2.5 ECN 18, the LBP pattern in tables 41 and 42 were changed but a number of LBP references were not, including:
 - a. The COMP data pattern definition, which includes the LBP pattern was not.
 - b. A pattern dependent note in the LBP definition is no longer applicable
 - c. Text definition of LBP is in two places

To maintain a consistent and unambiguous definition and usage of LBP, these references should be corrected.

1.2 Solution:

- 1) Replace the original 1 Dword LBP pattern in both the + and – disparity COMP data pattern definition with the updated 2 Dword LBP pattern. Additionally, since the new LBP pattern is twice the length, the repeat count for LBP in both the long and the short COMP pattern is cut in half.
- 2) Remove the Note at the end of section 7.2.4.3.5
- 3) Remove the redundant text from section 7.2.4.3, paragraph e) for two reasons:
 - a. The detailed pattern description is already covered by Section 7.2.4.3.5
 - b. Make it consistent with the other paragraphs of section 7.2.4.3.

1.3 Background – Original SATA 2.5 – ECN 18

Section 7.2.4.3.5

The lone-bit patterns, shown in Figure 92 and Figure 93, are comprised of the combination of adjacent 10B patterns, resulting in a lone one bit prefixed by a run length of four zeros, and suffixed by a run length of three zeros. It also results in a lone zero bit prefixed by a run length of two ones, one zero, two ones, one zero, four ones, and suffixed by a single one.

LBP Starting with RD-

Transmission order

-	D12.0(0Ch)-			D11.4(8Bh)+		D12.0(0Ch)-			D11.3(6Bh)+		+
	0011	0110	1111	0100	0010	0011	0110	1111	0100	0011	
	3	6	F	4	2	3	6	F	4	3	
+	D12.0(0Ch)+			D11.4(8Bh)-		D12.0(0Ch)+			D11.3(6Bh)-		-
	0011	0101	0011	0100	1101	0011	0101	0011	0100	1100	
	3	5	3	4	D	3	5	3	4	C	

Figure 92 – Lone-Bit Pattern (LBP) starting with RD-

Long version total: 1 * 2048 = 2048 Dwords

Short version total: 1 * 128 = 128 Dwords

LBP Starting with RD+

Transmission order

+	D12.0(0Ch)+			D11.4(8Bh)-		D12.0(0Ch)+			D11.3(6Bh)-		-
	0011	0101	0011	0100	1101	0011	0101	0011	0100	1100	
	3	5	3	4	D	3	5	3	4	C	
-	D12.0(0Ch)-			D11.4(8Bh)+		D12.0(0Ch)-			D11.3(6Bh)+		+
	0011	0110	1111	0100	0010	0011	0110	1111	0100	0011	
	3	6	F	4	2	3	6	F	4	3	

Figure 93 – Lone-Bit Pattern (LBP) starting with RD+

Long version total: 1 * 2048 = 2048 Dwords

Short version total: 1 * 128 = 128 Dwords

2 Technical Specification Changes

2.1 COMP table updates

Table 43 – Composite-Bit Pattern (COMP) Starting with RD–

Transmission Order →											
-	D31.3(7Fh)-		D31.3(7Fh)+			D31.3(7Fh)-		D31.3(7Fh)+			-
	1010	1100	1101	0100	1100	1010	1100	1101	0100	1100	
	A	C	D	4	C	A	C	D	4	C	
Above Dword is repeated a total of 256 times for long version. Above Dword is repeated a total of 16 times for short version.											
-	D21.5(B5h)-		D21.5(B5h)-			D21.5(B5h)-		D21.5(B5h)-			-
	1010	1010	1010	1010	1010	1010	1010	1010	1010	1010	
	A	A	A	A	A	A	A	A	A	A	
Above Dword is repeated a total of 64 times for long version. Above Dword is repeated a total of 4 times for short version.											
-	D24.3(78h)-		D24.3(78h)+			D24.3(78h)-		D24.3(78h)+			-
	1100	1100	1100	1100	1100	1100	1100	1100	1100	1100	
	C	C	C	C	C	C	C	C	C	C	
Above Dword is repeated a total of 64 times for long version. Above Dword is repeated a total of 4 times for short version.											
-	D10.2(4Ah)-		D10.2(4Ah)-			D10.2(4Ah)-		D10.2(4Ah)-			-
	0101	0101	0101	0101	0101	0101	0101	0101	0101	0101	
	5	5	5	5	5	5	5	5	5	5	
Above Dword is repeated a total of 64 times for long version. Above Dword is repeated a total of 4 times for short version.											
-	D25.6(D9h)-		D6.1(26h)+			D25.6(D9h)-		D6.1(26h)+			-
	1001	1001	1001	1001	1001	1001	1001	1001	1001	1001	
	9	9	9	9	9	9	9	9	9	9	
Above Dword is repeated a total of 64 times for long version. Above Dword is repeated a total of 4 times for short version.											
-	D17.7(F1h)-		D30.7(FEh)+			D7.1(27h)+		D14.7(EEh)+			-
	1000	1101	1110	0001	1110	0001	1110	0101	1100	1000	
	8	D	E	1	E	1	E	5	C	8	
Above Dword is repeated a total of 64 times for long version. Above Dword is repeated a total of 4 times for short version.											
-	D30.7(FEh)-		D7.6(C7h)-			D30.3(7Eh)-		D30.3(7Eh)+			-
	0111	1000	0111	1000	0110	0111	1000	1110	0001	1100	
	7	8	7	8	6	7	8	E	1	C	
Above Dword is repeated a total of 64 times for long version. Above Dword is repeated a total of 4 times for short version.											
-	D30.3(7Eh)-		D30.3(7Eh)+			D30.3(7Eh)-		D30.3(7Eh)+			-

Transmission Order →												
Above Dword is repeated a total of 64 times for long version. Above Dword is repeated a total of 4 times for short version.												
-	D24.3(78h)-			D24.3(78h)-			D24.3(78h)-			D24.3(78h)-		-
	1100	1100	1100	1100	1100	1100	1100	1100	1100	1100	1100	
	C	C	C	C	C	C	C	C	C	C	C	
Above Dword is repeated a total of 64 times for long version. Above Dword is repeated a total of 4 times for short version.												
-	D10.2(4Ah)-			D10.2(4Ah)-			D10.2(4Ah)-			D10.2(4Ah)-		-
	0101	0101	0101	0101	0101	0101	0101	0101	0101	0101	0101	
	5	5	5	5	5	5	5	5	5	5	5	
Above Dword is repeated a total of 64 times for long version. Above Dword is repeated a total of 4 times for short version.												
-	D25.6(D9h)-			D6.1(26h)+			D25.6(D9h)-			D6.1(26h)+		-
	1001	1001	1001	1001	1001	1001	1001	1001	1001	1001	1001	
	9	9	9	9	9	9	9	9	9	9	9	
Above Dword is repeated a total of 64 times for long version. Above Dword is repeated a total of 4 times for short version.												

Long version total: 2048 Dwords total
256DW SSOP
256DW HTDP (64DW, 64DW, 64DW, 64DW)
512DW LTDP (1DW, 1DW, 509DW, 1DW)
256DW LBP ((1DW, 1DW) x 128)
512DW LFSCP (255DW, 1DW, 255DW, 1DW)
256DW HTDP (64DW, 64DW, 64DW, 64DW)

Short version total: 128 Dwords total
16DW SSOP
16DW HTDP (4DW, 4DW, 4DW, 4DW)
32DW LTDP (1DW, 1DW, 29DW, 1DW)
16DW LBP ((1DW, 1DW) x 8)
32DW LFSCP (15DW, 1DW, 15DW, 1DW)
16DW HTDP (4DW, 4DW, 4DW, 4DW)

Table 44 – Composite-Bit Pattern (COMP) Starting with RD+

Transmission Order →													
+	D31.3(7Fh)+			D31.3(7Fh)-			D31.3(7Fh)+			D31.3(7Fh)-		+	
	0101	0011	0010	1011	0011	0101	0011	0010	1011	0011			
	5	3	2	B	3	5	3	2	B	3			
Above Dword is repeated a total of 256 times for long version. Above Dword is repeated a total of 16 times for short version.													
+	D21.5(B5h)+			D21.5(B5h)+			D21.5(B5h)+			D21.5(B5h)+		+	
	1010	1010	1010	1010	1010	1010	1010	1010	1010	1010	1010		
	A	A	A	A	A	A	A	A	A	A	A		

Transmission Order →

Above Dword is repeated a total of 64 times for long version.
Above Dword is repeated a total of 4 times for short version.

+	D24.3(78h)+		D24.3(78h)+			D24.3(78h)+		D24.3(78h)+			+
	0011	0011	0011	0011	0011	0011	0011	0011	0011	0011	
	3	3	3	3	3	3	3	3	3	3	

Above Dword is repeated a total of 64 times for long version.
Above Dword is repeated a total of 4 times for short version.

+	D10.2(4Ah)+		D10.2(4Ah)+			D10.2(4Ah)+		D10.2(4Ah)+			+
	0101	0101	0101	0101	0101	0101	0101	0101	0101	0101	
	5	5	5	5	5	5	5	5	5	5	

Above Dword is repeated a total of 64 times for long version.
Above Dword is repeated a total of 4 times for short version.

+	D25.6(D9h)+		D6.1(26h)+			D25.6(D9h)+		D6.1(26h)+			+
	1001	1001	1001	1001	1001	1001	1001	1001	1001	1001	
	9	9	9	9	9	9	9	9	9	9	

Above Dword is repeated a total of 64 times for long version.
Above Dword is repeated a total of 4 times for short version.

+	D14.7(Eeh)+		D30.7(Feh)-			D7.6(C7h)+		D17.7(F1h)-			+
	0111	0010	0001	1110	0001	1110	0001	1010	0011	0111	
	7	2	1	E	1	E	1	A	3	7	

+	D30.7(Feh)+		D7.1(27h)+			D30.3(7Eh)+		D30.3(7Eh)-			+
	1000	0111	1000	0111	1001	1000	0111	0001	1110	0011	
	8	7	8	7	9	8	7	1	E	3	

+	D30.3(7Eh)+		D30.3(7Eh)-			D30.3(7Eh)+		D30.3(7Eh)-			+
	1000	0111	0001	1110	0011	1000	0111	0001	1110	0011	
	8	7	1	E	3	8	7	1	E	3	

Above Dword is repeated a total of 509 times for long version.
Above Dword is repeated a total of 29 times for short version.

+	D28.7(FCh)+		D3.7(E3h)-			D28.7(FCh)+		D3.7(E3h)-			+
	0011	1000	0111	0001	1110	0011	1000	0111	0001	1110	
	3	8	7	1	E	3	8	7	1	E	

+	D12.0(0Ch)+		D11.4(8Bh)-			D12.0(0Ch)+		D11.3(6Bh)-			-
	0011	0101	0011	0100	1101	0011	0101	0011	0100	1100	
	3	5	3	4	D	3	5	3	4	C	

Transmission Order →

-	D12.0(0Ch)-		D11.4(8Bh)+			D12.0(0Ch)-		D11.3(6Bh)+			+
	0011	0110	1111	0100	0010	0011	0110	1111	0100	0011	
	3	6	F	4	2	3	6	F	4	3	
<p>Above 2 Dwords are repeated a total of 128 times for long version. Above 2 Dwords are repeated a total of 8 times for short version.</p>											
+	D11.5(ABh)+		D11.5(ABh)+			D11.5(ABh)+		D11.5(ABh)+			+
	1101	0010	1011	0100	1010	1101	0010	1011	0100	1010	
	D	2	B	4	A	D	2	B	4	A	
<p>Above Dword is repeated a total of 255 times for long version. Above Dword is repeated a total of 15 times for short version.</p>											
+	D11.5(ABh)+		D11.7(EBh)+			D20.2.(54h)-		D20.2(54h)-			-
	1101	0010	1011	0100	1000	0010	1101	0100	1011	0101	
	D	2	B	4	8	2	D	4	B	5	
<p>Above Dword is repeated a total of 255 times for long version. Above Dword is repeated a total of 15 times for short version.</p>											
-	D20.2(54h)-		D20.2(54h)-			D20.2(54h)-		D20.2(54h)-			-
	0010	1101	0100	1011	0101	0010	1101	0100	1011	0101	
	2	D	4	B	5	2	D	4	B	5	
<p>Above Dword is repeated a total of 255 times for long version. Above Dword is repeated a total of 15 times for short version.</p>											
-	D20.2(54h)-		D20.7(F4h)-			D11.5(ABh)+		D11.5(ABh)+			+
	0010	1101	0100	1011	0111	1101	0010	1011	0100	1010	
	2	D	4	B	7	D	2	B	4	A	
<p>Above Dword is repeated a total of 255 times for long version. Above Dword is repeated a total of 15 times for short version.</p>											
+	D21.5(B5h)+		D21.5(B5h)+			D21.5(B5h)+		D21.5(B5h)+			+
	1010	1010	1010	1010	1010	1010	1010	1010	1010	1010	
	A	A	A	A	A	A	A	A	A	A	
<p>Above Dword is repeated a total of 64 times for long version. Above Dword is repeated a total of 4 times for short version.</p>											
+	D24.3(78h)+		D24.3(78h)+			D24.3(78h)+		D24.3(78h)+			+
	0011	0011	0011	0011	0011	0011	0011	0011	0011	0011	
	3	3	3	3	3	3	3	3	3	3	
<p>Above Dword is repeated a total of 64 times for long version. Above Dword is repeated a total of 4 times for short version.</p>											

Transmission Order →											
+	D10.2(4Ah)+		D10.2(4Ah)+			D10.2(4Ah)+		D10.2(4Ah)+			+
	0101	0101	0101	0101	0101	0101	0101	0101	0101	0101	
	5	5	5	5	5	5	5	5	5	5	
Above Dword is repeated a total of 64 times for long version. Above Dword is repeated a total of 4 times for short version.											
+	D25.6(D9h)+		D6.1(26h)+			D25.6(D9h)+		D6.1(26h)+			+
	1001	1001	1001	1001	1001	1001	1001	1001	1001	1001	
	9	9	9	9	9	9	9	9	9	9	
Above Dword is repeated a total of 64 times for long version. Above Dword is repeated a total of 4 times for short version.											

Long version total: 2048 Dwords total
 256DW SSOP
 256DW HTDP (64DW, 64DW, 64DW, 64DW)
 512DW LTDP (1DW, 1DW, 509DW, 1DW)
 256DW LBP ((1DW, 1DW) x 128)
 512DW LFSCP (255DW, 1DW, 255DW, 1DW)
 256DW HTDP (64DW, 64DW, 64DW, 64DW)

Short version total: 128 Dwords total
 16DW SSOP
 16DW HTDP (4DW, 4DW, 4DW, 4DW)
 32DW LTDP (1DW, 1DW, 29DW, 1DW)
 16DW LBP ((1DW, 1DW) x 8)
 32DW LFSCP (15DW, 1DW, 15DW, 1DW)
 16DW HTDP (4DW, 4DW, 4DW, 4DW)

Note that only 128 Dwords total for the composite pattern is too short to get a sufficient number of continuous repeats for each pattern type.

2.2 Section 7.2.4.3.5 Note removal

Remove the last paragraph NOTE from section 7.2.4.3.5 as the new LBP no longer has a starting disparity dependency as long as the complete (2 Dwords) LBP is use .

Text to be removed:

~~NOTE: Care should be taken when generating the lone-bit pattern. Two potential patterns are available: 8Bh_0Ch_8Bh_0Ch if the initial running disparity is positive (RD+) or 0Ch_8Bh_0Ch_8Bh if the initial running disparity is negative (RD-). It is important that the selected pattern match the initial running disparity or else the encoded pattern will not match the desired lone-bit pattern. For example, if 8Bh_0Ch_8Bh_0Ch is transmitted when the initial running disparity is negative, the encoded data will not match the desired lone-bit pattern. A similar mismatch will occur if the 0Ch_8Bh_0Ch_8Bh pattern is transmitted when the initial running disparity is positive.~~

2.3 Section 7.2.4.3 – paragraph e)

Section 7.2.4.3 paragraph e) contains a redundant text definition of LBP (section 7.2.4.3.5) and for consistency with other paragraphs of section 7.2.4.3, the following change should be made:

- e) The lone-bit patterns (LBP) are comprised of the consecutive combination of certain 10b patterns that result in a lone-bit. ~~More specifically, a lone-bit is prefixed by a run-length of four bits and followed by a run-length of three or prefixed by a run-length of two ones, one zero, two ones, one zero, four ones, and suffixed by a single one.~~ These patterns create a condition where the preceding 4-bit run-length results in minimum amplitude of the lone-bit as well as its time-width in comparison to its surrounding segments. This is often the worst case condition that the receiving data recovery circuits may encounter.